

NOTES:


- 1.THIS FIGURE IS THE PREFERRED SECONDARY TERMINATION FOR SINGLE-PHASE PAD-MOUNT TRANSFORMERS.
- 2. USE JAM NUT TO LOCK ALL SCREW ON CONNECTORS ON TRANSFORMER SECONDARY STUD.

## FIGURE 1

TRANSFORMER kVA	MAX ALLOWED SERVICE CABLES / CONDUITS PER LEG**	SECONDARY CONNECTOR TEC NO.	CABLE RANGE CU. OR AL.	CONNECTOR DESCRIPTION	
25 THRU 75	(8) SETS OF 3 WIRE OR 4 WIRE IN 2" CONDUIT MAX OR (6) SETS OF 3 WIRE OR 4 WIRE IN 3" CONDUIT MAX OR (4) SETS OF 3 WIRE OR 4 WIRE IN 4" CONDUIT MAX	2004948	#10-350 kCMIL	6 TAPS, 🗞" - 11	THREADS
		2004954	#6-500 kCMIL	6 TAPS, 🗞" - 11	THREADS
		2004902	1/0-750 kCMIL**	6 TAPS, ⅔" - 11	THREADS
		2004950	#6-250 kCMIL	8 TAPS, 🗞" - 11	THREADS
		2004904	#6-500 kCMIL	8 TAPS, ⅔" - 11	THREADS
100 THRU 250	(8) SETS OF 3 WIRE OR 4 WIRE IN 2" CONDUIT MAX OR (6) SETS OF 3 WIRE OR 4 WIRE IN 3" CONDUIT MAX OR (4) SETS OF 3 WIRE OR 4 WIRE IN 4" CONDUIT MAX	2004952	#2-500 kCMIL	6 TAPS, 1" - 14	THREADS
		2004901	1/0-750 kCMIL**	6 TAPS, 1" - 14	THREADS
		2004903	#2-500 kCMIL	8 TAPS, 1" - 14	THREADS

## NOTES:

- 1. THE MAXIMUM ALLOWED SERVICE CABLES PER LEG DOES NOT INCLUDE AN ADDITIONAL STREETLIGHT TAP WHICH IS PROVIDED ON CONNECTORS.
- 2. IF THE NUMBER OF CABLES THE CONTRACTOR WISHES TO INSTALL EXCEEDS THE MAXIMUM ALLOWED SERVICE CABLES PER LEG, A TAMPA ELECTRIC PAD-MOUNTED SECONDARY TERMINATION CABINET TEC NO. 2004579 (REFER TO GR&S UG 12-26) OR A TAMPA ELECTRIC HANDHOLE (REFER TO GR&S UG 9-7) MAY BE USED. INSTALLATION OF THE HANDHOLE AND CABLE CONNECTIONS WILL BE COMPLETED BY TAMPA ELECTRIC PERSONNEL AT THE CUSTOMER'S EXPENSE.
- \*\* CONTRACTORS MUST OBTAIN TEC APPROVAL TO INSTALL CONNECTORS LARGER THAN 750 KCMIL.



7 RGH 8-26-21 REVISED NOTES IN COLUMN 2
6 SJH 11-07-19 ADDED NUMBER OF CONDUITS TO TABLE, UG GRS 11-1 REF.
5 RGH 6-04-19 REV. IN TABLE TX RANGE TO INCLUDE 250KVA. MODIFIED NOTES
4 SJH 7-20-16 REV. IN TABLE CABLE RANGE FROM #6-500 KCMIL TO 1/0-750 KCMIL
NO. CK'D DATE REVISION

■ DENOTES LATEST REVISION

MGR; STD'S
APPR. DATE
SUPERSEDES
SUPERSED
SUPERS
SUPERSED
SUPERSED
SUPERSED
SUPERSED
SUPERSED
SUPERSED
SUPERSED

11 - 2

SECONDARY CONNECTORS
SINGLE-PHASE URD PAD-MOUNT TRANSFORMER

TAMPA ELECTRIC CO.

STANDARDS

GENERAL RULES & SPECIFICATIONS UG.